



Compatible Dimmer List



MEGAMAN® LED PAR16 Reflector 6W
LR1206dLNv2-FL, LR1206dLNv2-WFL and
LR1206dDGv2-VWFL

Dimmer List 220-240V

Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
Altenburger	EHR600W	220-240	60-600	1	6
Broco	F25AF	220-240	60-500	1	4
Busch	2210	230	60-400	1	6
Busch	2210-510	220-240	400	1	6
Busch	2250U	230	600	1	6
Busch	2210 U	230	60-400	1	6
Chengli	27V500	250	500	1	6
Clipsal	32E2CFLDM	220-240	300	1	6
Clipsal	32V 500 series	220-240	500	1	3
Contactum	P400	216-253	60-400	1	6
Crabtree	CRO-1W400	220-240	10-600	1	6
Danlers	DG05014	230	60-400	1	6
Dimmalite	EUR400	230	60-400	1	6
Doyle & Tratt Products	7066	220-240	40-250	1	6
Elko	400GLI	220-240	40-400	1	6
Era	DG07037	220-240	300	1	6
Everfourish	EF0700DA	220-240	50-300	1	6
Fungyip	F2771	220-240	500	1	6
Garieg	DG04043	220-240	200	1	2
GET	GET 60-400W	220-240	60-400	1	6
Hamilton	L400/2	220-240	400	1	4
Igoto	DG04041	220-240	200	1	4
Jin Meung (SK)	DG04047	220-240	630	1	6
Keytop	BP1000	220-240	1000	1	4
Legrand	ADWGL4	220-240	40-400	1	6
Legrand	Haut 100-1000VA	250	100-1000	1	6
Legrand	Mosaic	220-240	60-500	1	6



Manufacturer	Model No.	Voltage (V)	Wattage (W)	Min. Number of LED Lamp(s) Compatible*	Max. Number of LED Lamp(s) Compatible*
Merlin Gurin	MGU351118	230	400	1	6
MK	42804PL	230	40-250	1	6
MK	GX8051	220-240	40-500	1	6
MK	SX8051	240	40-500	1	3
National	WEG57515	220-240	40-500	1	6
National	WNG6801	220-240	500	1	3
Niko	310-016	220-240	50-500	1	6
POL	CAT 1593M	220-240	500	1	6
Relco	RM0736	220-240	60-500	1	6
Richmond	GRID400CFL	240	400	1	6
Richmond	GRID500	240	40-500	1	6
Schneider	SD300	220-240	300	1	6
Sicherung	Grundtyp H1	230	25-500	1	1
Simon	Simon..813	220-240	40-500	1	6
Switchlight	SW-316	220-240	500	1	2
T&J	K211-M2 6L29	230	40-630	1	1
T&J	P2017S	220-240	40-630	1	4
Venus	9720	220	40-900	1	5
Viko	90 30 48	220	600	1	6
Vimar	14150	230	100-500	1	6
Vivian	D-21102	220-240	1000	1	6
Wonpro	WF Series	250	500	1	5

Remarks: *The minimum and maximum number of LED lamps compatible depends upon the performance of the dimmer, which is subject to the status of the manufacturer's technology. Due to possible variations in country dimmer module specifications, please contact your local distributor for a list of compatible dimmers before installation. Copyright © MEGAMAN® 2012. All rights reserved.

All the information contained within this publication was correct at the time of update and is subject to change without prior notice. All other trademarks mentioned are the property of their respective owners.